## Product card



Symbol: AX-101B
Manufacturer: AXIOMET

**Product groups:** Portable digital multimeters

## **Product specifications**

Meter type:	digital multimeter		
Measuring instrument features:	<ul> <li>diode and continuity test with buzzer</li> <li>low battery indicator</li> <li>manual ranging</li> <li>shock-resistant case</li> <li>square waveform generator</li> <li>LCD display with backlight</li> </ul>		
Type of display used:	LCD 3,5 digit (1999)		
Sampling:	2-3x/s		
DC voltage measuring range:	100μ200m/2/20/200/500V		
DC voltage measuring accuracy:	±(0,5% + 2 digits)		
AC voltage measuring range:	100m200/500V		

$\overline{}$					
ы	rn	Иı	ICT	ca	ra

1 Todact card				
AC voltage measuring accuracy:	±(1,2%+ 10 digits)			
DC current measuring range:	1μ2m/20m/200m/10A			
DC current measuring accuracy:	±(1% + 2 digits)			
Resistance measuring range:	0,1200/2k/20k/200k/20M/200MΩ			
Resistance measuring accuracy:	±(0,8% + 2 digits)			
Continuity test:	acoustic signal for R			
Operating temperature:	040 °C			
Overall dimensions (W x D x H):	74 x 35 x 150 mm			
Weight with battery:	156 g			
Power supply:	1 battery 9V 6F22			
Standard equipment:	<ul><li>test leads</li><li>user's manual</li></ul>			

## **Additional information**

Gross weight:	156.00 g
Quantity in collective	1
package [pcs]:	