

### **FR** series


### **Fusible Metal Film Resistors**

#### Features

- » Suitably used in transistor protection circuit
- » Small in size
- » Noncombustible insulating coating; "Solvent" proof and resistant to high temperature
- » Low temperature coefficient (±200ppm ~ ±350ppm/℃)
- » Uniform in fusing time



#### Dimensions



TYPE Normal	TYPE Mini.	DIMENSION (mm)				RESISTANCE RANGE
		L	ΦD	Н	d(±0.05)	
FR25	FRS50	6.3±0.5	2.3±0.3	28±3	0.55	0.5 $\Omega$ -10K $\Omega$
FR50	FRS100	9.0±0.5	3.2±0.5	28±3	0.55	0.5 $\Omega$ -10K $\Omega$
FR100	FRS200	11.5±1.0	4.5±0.5	28±3	0.60	0.5 $\Omega$ -10K $\Omega$
FR200	FRS300	15.5±1.0	5.0±0.5	32±2	8.0	0.5 $\Omega$ -10K $\Omega$

RCWV= √Rated Power X Resistance Value
Max Overload voltage is 2 times of Max Working Voltage
Out of the resistance range is available on request.

Tel: 886-2-8221-2898 E-MAIL: faithful@faithfullink.com Website: www.faithfullink.com



### **♦ Part Number**

FR	100	J	2R3	Т
Туре	Watt	Tolerance	R value	Packing
FR	1/4W = 25	J = ± 5%	2.3Ω= 2R3	T = Taping Box
FRS	1/2W = 50	G = ± 2%	$1K\Omega = 1K$	B = Bulk
	1W = 100	F = ± 1%		R = Taping Reel
	2W = 200			M = M Type
	3W = 300			MB = MB Lead Form
				MK = MK Lead Form
				F = F Lead Form
				FC = FC Lead Form
				FCK = FCK Lead Form
				FKK = FKK Lead Form

## **♦** Electrical Characteristics

TEMPERATURE COEFFICIENT	±200~350ppm
SHORT TIME OVERLOAD	±(2%+0.05Ω)
INSULATION RESISTANCE MIN DRY	1000ΜΩ
LOAD LIFE	±(5%+0.05Ω)
TERMINAL STRENGTH	Tensile: <u>≥</u> 2.5kg
SOLDERABILITY	95% min overage
DIELECTRIC WITHSTANDING VOLTAGE	<u>≥</u> 500V
OPERETING TEMPERATURE RANGE	−40°C TO +155°C
TOLARANCE	±5%, ±2%, ±1%
SELECTION SERIES	E-24

Tel: 886-2-8221-2898 E-MAIL: faithful@faithfullink.com Website: www.faithfullink.com




# **♦** Fusing Characteristics


POWER RATING	FUSING TIME			
FOWER RATING	TYPICAL (Sec.)	MAXIMUM (Sec.)		
16 X Wattage	30	60		
20	20	40		
24	10	30		
28	8	20		
32	5	15		

# Lead Forming


**M Lead Form** 








**MB Lead Form** 





**MK Lead Form** 







F Lead Form








**FCK Lead Form** 





**FKK Lead Form** 

3

Tel: 886-2-8221-2898 E-MAIL: faithful@faithfullink.com Website: www.faithfullink.com